

# INVERTER GENERATOR MODEL COMPARISON

## ALL DENQBAR PRODUCTS AT A GLANCE

All the advantages, all the performance levels in one overview, so that you can choose your right DENQBAR generator. When making your selection, pay attention to the consumers you connect and which comfort features you want, such as portability or digital display. All our power generators offer the advantage of the new inverter technology, optimum voltage stability without strong frequency fluctuations.



Equipment	DQ-2000	DQ-2100	DQ-4200
Max AC output (230 V)	2000 W	2100 W	4200 W
Rated AC output (230 V)	1800 W	1800 W	3800 W
Voltage regulation	Inverter	Inverter	Inverter
Socket	1 x 230 V, 1 x 12 V, 2 x USB	1 x 230 V, 1 x 12 V, 2 x USB	2 x 230 V, 1 x 12 V, 2 x USB
DC output	12 V / 8,3 A charging current	12 V / 8,3 A charging current	12 V / 8,3 A charging current
Noise level (idle)	55 dB (A)/7m	55 dB (A)/7m	63 dB (A)/7m
Engine	4-cycle, OHV, Single cylinder	4-cycle, OHV, Single cylinder	4-cycle, OHV, Single cylinder
Displacement	80 cm <sup>3</sup>	79,7 cm <sup>3</sup>	223 cm <sup>3</sup>
Fuel	petrol	petrol	petrol
Degree of protection	IP23M	IP23M	IP23M
Tank capacity	4 l	4 l	11 l
Run time	up to 6 h	up to 6 h	up to 10 h
Dimensions L x W x H	50 cm x 29,5 cm x 47,5 cm	49,8 cm x 29,8 cm x 45,9 cm	60,5 cm x 43,2 cm x 50 cm
Weight	22 kg	22 kg	42 kg
Oil deficiency indicator	Yes	Yes	Yes
Overload indicator	Yes	Yes	Yes
Recoil starter	Yes	Yes	Yes
Electric start	No	No	No
Remote control	No	No	No
Petrol-saving mode	Yes	Yes	Yes
Wheel set	No	No	No
Digital display	No	Yes	No
Operating hours counter	No	Yes	No